




by **Schneider** Electric



# Mains Connection Box

## 651A2 & 651A3 Series

### Wiring Instructions

1. **'CONSUMER' CABLES** 35mm<sup>2</sup> for 90Amp or 25mm<sup>2</sup> for 70Amp copper must be properly spaced and securely fixed into the **LEFT** terminal of each phase.

**Note:** **'SUPPLY'** terminals have **CAPS** fitted above for convenient identification.

2. **'SUPPLY' ACTIVES** enter through holes beneath the **RIGHT** terminal of each phase.  
**'SUPPLY' NEUTRAL** in central cut-out at either end, or as determined by authority.

## IMPORTANT

1. The insulating washers supplied **must be** fitted under the mounting bolts' heads.
2. When tightened, the bolt head **must be** covered with the moulded caps supplied for double insulation.
3. Caps **must be** securely glued to the washers and base with PVC cement.

---

**Schneider Electric (Australia) Pty Ltd**

**clipsal.com**

Contact us [clipsal.com/feedback](http://clipsal.com/feedback)

**National Customer Service Enquiries:**

**Tel 1300 2025 25      Fax 1300 2025 56**

Schneider Electric (Australia) Pty Ltd reserves the right to change specifications, modify designs and discontinue items without incurring obligation and whilst every effort is made to ensure that descriptions, specifications and other information in this catalogue are correct, no warranty is given in respect thereof and the company shall not be liable for any error therein.

© 2011 Schneider Electric. All Rights Reserved.

Trademarks are owned by Schneider Electric Industries SAS or its affiliated companies