



NOTES:

1. INSTALLATION SHALL COMPLY WITH ALL APPLICABLE NATIONAL AND LOCAL CODES.
2. SEE PRODUCT DOCUMENTATION FOR FURTHER INFORMATION PRIOR TO INSTALLATION.
- △3. UTILITY SOURCE MUST BE 2WIRE+GROUND, PROVIDED BY OTHERS. RECOMMENDED INPUT BRANCH CIRCUIT BREAKER RATINGS FOR SINGLE-PHASE INPUT, 60A; FOR TWO-PHASE INPUT, 30A.
- △4. DASHED LINES (- - -) REPRESENT CABLING PROVIDED BY OTHERS.
5. RECOMMENDED MAXIMUM OUTPUT BREAKER RATING IS 60A. MAXIMUM VA IS LIMITED TO 10kVA.
- △6. TABLE:

INPUT NO OF PHASE	INPUT VOLTAGE (AC)		OUTPUT VOLTAGE AT 60A (10kVA UNITS) TERMINAL BLOCK CONNECTIONS			
	SWITCH POSITION	SWITCH CONTACTS (CLOSE POSITION)	7, 10	7, 9	8, 10	8, 7
SINGLE PHASE	200-240	1-2, 5-6, 13-14	200/240V	208V	100/120V	100/120V
	208V	3-4, 7-8, 13-14	240V	208V	120V	120V
TWO PHASE	400V	3-4, 11-12	220-240V	--	--	--
	480V	1-2, 9-10	240V	208V	120V	120V

- △7. THE GROUND ELECTRODE CONDUCTOR IS PROVIDED BY OTHERS.

THIS DRAWING AND SPECIFICATIONS HEREIN ARE THE PROPERTY OF SCHNEIDER ELECTRIC AND SHALL NOT BE COPIED, REPRODUCED OR USED IN WHOLE OR IN PART, AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION FROM SCHNEIDER ELECTRIC. THIS DRAWING IS BASED UPON LATEST AVAILABLE INFORMATION AND IS SUBJECT TO CHANGE WITHOUT NOTICE.



TITLE:
STEP-DOWN TRANSFORMER
INPUT: 208VAC, 1 ϕ OR 480VAC, 2 ϕ
OUTPUT: 10kVA, 120VAC OR 208VAC
SYSTEM WIRING DIAGRAM

PROJECT: STD SUBMITTAL DRAWINGS SHEET 1 OF 1

DWG NO: APTF10KT01-WD REV. 1
DRAWN BY: JAYAPRAKASH/S CUNHA 23-MAY-12 PROJ
ENGINEER: K WHITE/B BUNGCAYAO 13-SEP-07 ANGLE
APPROVED BY: M TAVARES 13-SEP-07 N/A