Product data sheet
Characteristics

T40BG120BDDAP1S6
SZ0 FVNR COMBO 1 SC DEV FLA 4.5-18

Commercial status
This Product is Obsolete :

⚠ This Product is Obsolete

Main

Product or Component Type	Self-protected combination motor controller
Range of Product	TeSys N Self-Protected Combination Motor Controller
Product Certifications	CSA[RETURN]UL Listed
Control circuit	Separate control circuit
Provided Equipment	Current limiter
Phase	3 phase
[Ue] rated operational voltage	600 V AC
[Uc] control circuit voltage	24 V DC
Communication port protocol	DeviceNet
NEMA Degree of Protection	NEMA 1
Enclosure Material	Painted sheet steel
Enclosure type	Standard size
Enclosure accessory description	With external reset
Auxiliary contact composition	1 NO + 1 NC
NEMA size	0
Maximum Horse Power Rating	5 Hp 460 V AC 3 Hp 230 V AC 3 Hp 200 V AC 5 Hp 575 V AC
Poles description	3P
Local signalling	Red indicator on LED
Control type	Push-button START-STOP)
Motor starter type	Non reversing
Electrical Connection	Screw-clamp terminals
Thermal overload type	Solid state advanced class 20 4.5…18 A
Disconnector device type	Self-protected combination controller 18 A

Ordering and shipping details

Category	21219-ENCLOSED TESYS N COMB STR SIZE 1
Discount Schedule	CP1
Returnability	No

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Weight	24.62 Lb(US) (11.167 kg)

Contractual warranty

Warranty	18 months

Product Life Status : End of commerc. - Block

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein.
This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications.
It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof.
Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.