



SQUARE D COMPANY

THIS TYPE 4,4X ENCLOSURE MAY BE USED WITH THE DEVICES LISTED BELOW

| ENCLOSURE | FOR USE WITH | | | GROUNDING KITS | |
|----------------|-----------------|-------------------------|--------------|----------------|---------------------|
| | CLASS 9991 TYPE | NEMA SIZE OR AMP RATING | CLASS * TYPE | NO. OF POLES | USE CLASS 9999 TYPE |
| SCW-1, -11 * | 0 | 8502 | SBO | 2, 3 | GBK24 |
| | | | SCO | 4, 5 | GBK34 |
| SDW-1, -11 * | 2 | | SDO | 2, 3 | GBK24 |
| | | | | 4, 5 | GBK34 |
| SEW-1, -11 * | 3 | | SEO | 2, 3 | GBK22 |
| | | | | 4, 5 | GBK22 & GBK32 |
| SFW-11 * | 4 | | SFO | 2, 3 | GBK22 |
| | | | | 4, 5 | GBK22 & GBK32 |
| SCW-1, -11 + | 0 | 8536 | SBO | 2, 3 | GBK24 |
| | | | SCO | 4 | GBK34 |
| SDW-1, -11 % + | 2 | | SDO | 2, 3 | GBK24 |
| | | | | 4 | GBK34 |
| SEW-1, -11 # | 3 | | SEO | 2, 3 | GBK22 |
| | | | | 4 | GBK22 & GBK32 |
| SFW-11 # | 4 | | SFO | 2, 3 | GBK22 |
| | | | | 4 | GBK22 & GBK32 |
| SCW-1, -11 * | 30 AMP | 8903 | SMO | 2, 3 | GBK24 |
| | | | | 4 | GBK34 |
| SDW-1, -11 * | 20 AMP | | LO LXO | 2, 3 | GBK24 |
| | | | | 4, 6 | GBK34 |
| | | | | 8 | (2) GBK24 |
| | | | | 10, 12 | GBK24 & GBK34 |
| SEW-1, -11 * | 60 AMP | | SPO | 2, 3 | GBK24 |
| | | | | 4, 5 | GBK24 & GBK34 |
| SEW-1, -11 * | 100 AMP | SQO | 2, 3 | GBK22 | |
| | | | 4, 5 | GBK22 & GBK32 | |

+ Enclosure not suitable for starters with Form B20 through B42.

Enclosure suitable for starters with melting alloy overload relay only.

* For contactors, replace reset assembly with closing plate, Class 9001, Type K52.

% Enclosure not suitable for use with Class 8536 Type SDO-8 Starters.