

CLIPSAL CAT. NO. 651A2/70 and 651A2/100

WIRING INSTRUCTIONS

1. **CONSUMERS CABLES** to be properly spaced and securely fixed into the **left** terminal of each **active** phase and **neutral** terminal.
2. **Additional consumer cables** may be used by **looping actives** (16mm² max.) and using **spare** hole in neutral terminal.
3. **SUPPLY CABLES** enter through cut outs on either end of box or as determined by authority. Securely fix into the **right terminal** of each **active** phase and **neutral** terminal.

IMPORTANT

Insulating caps and plugs supplied must be fitted over mounting bolt heads for double insulation.