



How to update EVlink Pro AC through EV Charging Expert

Technical Support eMobility

Life Is On

Schneider
Electric

Prerequisites:

Download the Pro AC firmware from [this webpage](#)

Unzip **this file** and use the **evlink-bundle-v1.3.6-official.raucb** for the next slide

EVlink Pro AC Firmware

Référence: GEX28844

EVlink Pro AC_charging station_Release_Note



firmware update from eSetup (USB).zip



firmware update from EVCE or OCPP.zip



UK only.zip



Télécharger

1st Step : Upload the Pro AC firmware into EV Charging Expert memory

Choose one **Pro AC** in the left part and click on “**upload a new firmware version**”

Write the new firmware version and **select the Pro AC firmware** (evlink-bundle-v1.3.6-official.rauch)

The screenshot displays the Schneider Electric EV Charging Expert web interface. On the left, a sidebar menu shows the 'ZONES' section expanded, with a list of charging stations. The station 'EVlink Pro AC - 20010 - Poolauto' is selected and highlighted with a blue border. The main panel shows the configuration for this station, including fields for Name, Charge Box Identity, and Authentication Mode. A green 'Firmware Upload' modal is open, containing fields for 'Charging Station Model', 'Current Version', and 'New Firmware Version'. The 'New Firmware Version' field is highlighted with a green border and contains the value '1.3.5'. Below it, a file selection field is highlighted with a red border, showing the file 'evlink-bundle-v1.3.5-official.rauch'. To the right of the modal, two buttons are visible: 'UPDATE FIRMWARE (1.2.1)' and 'UPLOAD A NEW FIRMWARE VERSION', with the latter button highlighted by a green rectangle. The bottom of the page features the Schneider Electric logo and the text 'Life Is On'.

Page 3

2nd step: Update each charging station

1. On the same Pro AC, **refresh the page** and click now on “**update firmware**”
2. Go to the **next charging station** in the left part, and click on “**update firmware**”
3. Apply the **same thing** for the **next charging stations**

The screenshot displays the Schneider Electric web interface for managing charging stations. The left sidebar shows a list of charging stations under the 'LVK laadpalen 1' category. The selected station is 'EVLink Pro AC - 20010 - Poolauto'. The main content area shows the configuration for this station, including fields for Name, Charge Box Identity, VIP, Authentication Mode, and Authentication When Disconnected. The Firmware version is 1.3.4, and the 'Update Firmware (1.3.5)' button is highlighted with a blue box. A green arrow points from the selected station in the sidebar to the 'Update Firmware (1.3.5)' button.

3rd step: Download a “Device Report” EV Charging Expert

After about 10-15 min, when the dashboard is stabilized, download a “Device Report” and check that all the charging stations are up-to-date

Charging stations

Active 38

Lost 0

Total 38

EVlink Pro AC

Admin

Configuration

User Management

Logs

Device Reports

Stations Report

Firmware Update

Licence Upgrade

Restart

TRI123	[EVlink Pro AC]	05:04:09	1.3.5	●
TRI123	[EVlink Pro AC]	05:05:03	1.3.5	●
TRI123	[EVlink Pro AC]	05:05:02	1.3.5	●
TRI231	[EVlink Pro AC]	05:05:02	1.3.5	●
TRI123	[EVlink Pro AC]	05:04:27	1.3.5	●
TRI123	[EVlink Pro AC]	05:04:27	1.3.5	●
TRI123	[EVlink Pro AC]	05:04:47	1.3.5	●
TRI231	[EVlink Pro AC]	05:04:09	1.3.5	●

Life Is On

