



### Main

For two BNC/TNC connectors Ø 12.5 mm or for BNC/TNC connectors Ø 9.5 mm.  
Second opening can be broken out.

### Complementary

Contents: With adjustment rings.

Colour: black

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.