



NOTES:

1. PLEASE REFER TO APC INSTALLATION GUIDE.
- △ 2. MUST BE 3x380/400/415V TN-S/TN-C/IT/TT (PROVIDED BY OTHERS).
3. ----- = AC/DC CABLING PROVIDED BY OTHERS.
4. ALL AC POWER CABLING IS L1,L2,L3,N,PE.
- △ 5. DC CABLING SHOULD BE SEGREGATED FROM AC CABLING SEE BATTERY INSTALLATION INFORMATION
6. UPS INPUT AND OUTPUT CABLES SHOULD BE SEGREGATED
7. POWER WIRING AND CONTROL WIRING SHOULD BE SEGREGATED
- △ 8. XR BATTERY CABINET CAN BE BAYED TO UPS. BAYING KIT HAS TO BE PURCHASED AS AN OPTION. XR BATTERY CABINET IS ALSO AVAILABLE WITHOUT BREAKER, WITH DC FUSES ONLY UP TO 4 XR BATTERY CABINETS CAN BE CONNECTED TO UPS TO EXTEND BACKUP TIME
- △ 9. SINGLE MAINS INSTALLATION IS A DEFAULT. FOR DUAL MAINS OPTION REFER TO DRAWING# SUVT15KH2S-SD FOR DETAILS
10. OUTPUT OVERCURRENT PROTECTION MUST BE PROVIDED BY OTHERS. RECOMMENDED OUTPUT BREAKER RATING 25A
11. INSTALLATION MUST COMPLY WITH NATIONAL AND LOCAL CODES.

THIS DRAWING AND SPECIFICATIONS HEREIN ARE THE PROPERTY OF AMERICAN POWER CONVERSION AND SHALL NOT BE COPIED, REPRODUCED OR USED IN WHOLE OR IN PART, AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION FROM APC. THIS DRAWING IS BASED UPON LATEST AVAILABLE INFORMATION AND IS SUBJECT TO CHANGE WITHOUT NOTICE.

TITLE: SMART-UPS VT
 INPUT: 3x380/400/415V SINGLE FEED
 OUTPUT: 3x380/400/415V 15kVA
 SYSTEM ONE LINE DIAGRAM
 PROJECT: SUBMITTAL DRAWING SHEET 1 OF 1

DWG NO: SUVT15KH1S-SD
 DRAWN: JAYAPRAKASH 23/08/05
 CHECKED: M.SALOKHE 23/08/05
 ENGINEER: S.WAGH 23/08/05

REV. 1
 PROJECTION

