



**NOTES:**

1. ALL DATA IN THIS DRAWING IS PROVIDED FOR A FULLY POPULATED UNIT.
- △2. AC SOURCE MUST BE 480VAC, WYE CONNECTED, 3W+G, EITHER SOLIDLY OR HIGH RESISTANCE GROUNDED (CONTACT Schneider Electric IF OTHER). REFER TO INSTALLATION MANUAL FOR UPSTREAM CIRCUIT BREAKER REQUIREMENTS.
- △3. DASHED LINES BETWEEN UNITS (---) REPRESENT AC/DC CABLING PROVIDED BY OTHERS.
4. ALL AC CIRCUIT BREAKERS ARE 100% CONTINUOUS DUTY RATED WITH 24VDC SHUNT TRIPS AND 2A/2B AUX CONTACTS.
5. Q1 = 1800AT/1800AF; Q2 = 1600AT/1600AF; Q3, Q4, Q5 & LBB = 3000AT/3000AF.
6. Q6 = 3000A (MINIMUM) MOLDED CASE SWITCH WITH 24VDC SHUNT TRIPS AND 2A/2B AUXILIARY CONTACTS.
7. Q7, Q8 = 1800AT DC RATED DISCONNECT WITH 24VDC UNDERVOLTAGE RELEASE (UVR) AND 2A/2B AUX CONTACTS.
- △8. OPTIONAL COMPONENTS.
- △9. SEPARATE CONDUITS. 2W+GND.
10. UPS INPUT AND OUTPUT CONDUCTORS MUST BE IN SEPARATE CONDUITS.
- △11. UPS AND STATIC BYPASS WITHSTAND 200,000 SYMMETRICAL AMPERES.
12. INSTALLATION SHALL COMPLY WITH ALL APPLICABLE NATIONAL, STATE AND LOCAL CODES.

THIS DRAWING AND SPECIFICATIONS HEREIN ARE THE PROPERTY OF SCHNEIDER ELECTRIC AND SHALL NOT BE COPIED, REPRODUCED OR USED IN WHOLE OR IN PART, AS THE BASIS FOR THE MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION FROM SCHNEIDER ELECTRIC. THIS DRAWING IS BASED UPON LATEST AVAILABLE INFORMATION AND IS SUBJECT TO CHANGE WITHOUT NOTICE.



TITLE: SYMMETRA MW  
480VAC, 3φ, 2x1200kW  
SINGLE FEED  
SYSTEM SINGLE-LINE DIAGRAM  
PROJECT: STD SUBMITTAL DRAWINGS | SHEET 1 OF 1

DWG NO: SYMF1200K2400G1C2-SD  
DRAWN BY: S CUNHA 30-JAN-14  
ENGINEER: C BARBOZA 30-JAN-14  
APPROVED BY: B SHERIDAN 30-JAN-14

REV: 4  
PROJ ANGLE: N/A