

U.Motion 7” Android 6 v2

The following document describes when this Firmware “Android 6 v2” should be installed and which devices are compatible with it. It’s recommended to read it before updating your device.

1. Affected products

Touch Panel Client	Commercial References	OS Version	Selling Date		Serial Number	
			Start	End	Start	End
U. Motion 7" V2/V3	MEG6260-0307 MTN6260-0307	Android 6	oct-18	ongoing	S3002702	ongoing

Make sure your Touch Panel has the OS described above (Android 6) and that the serial number is greater than S3002702.

Note: The new FW is NOT compatible with older devices with Android below 6.

2. When to use this new FW

The new **FW Android 6 v2** includes some updates in the browser and has been specifically created to offer better support of the new Touch 3.0 visualization of the Wiser for KNX and spaceLYnk controllers available in their FW 2.5.0 released on 30.06.2020.

Note: The new FW update is only needed in the following conditions are met:

- 1) If the Touch Panel is used together with a Wiser for KNX or spaceLYnk
- 2) If the Controllers have been updated or will be updated to support the new Touch 3.0 visualization (available in FW2.5.0 or through download in the controller’s marketplace)

If your installation doesn’t meet the 2 conditions above, then is NOT needed to be installed.

3. Update Procedure

1. Copy the file “U.Motion 7 in Android 6.0 FW v2.zip” into an SD card or USB stick
2. Configure one of launcher slots with an app called “System Update” (The App can be linked to a slot (free or occupied) on the Launcher by long-press on the slot.
3. Browse the file described in step 1 and select it
4. Click on the button named “Update using the specified update.zip file”

