



SQUARE D COMPANY

THIS TYPE 3R ENCLOSURE MAY BE USED WITH THE DEVICES LISTED BELOW

ENCLOSURE CLASS 9991 TYPE	FOR USE WITH				GROUNDING KITS USE CLASS 9999 TYPE	
	CLASS	TYPE	NO. OF POLES	NEMA SIZE OR AMP RATING		
SCH-2 *	8502	SBO	2, 3	0 & 1	GBK24	
		SCO	4, 5		GBK34	
SDH-1 *		SDO	2, 3	2	GBK24	
			4, 5		GBK34	
SEH-1 *		SEO	2, 3	3	GBK22	
			4, 5		GBK32	
SFH-1 *		SFO	2, 3	4	GBK22	
			4, 5		GBK32	
SCH-2 +		8536	SBO	2, 3	0 & 1	GBK24
			SCO	4		GBK34
SDH-1 +			SDO	2, 3	2	GBK24
				4		GBK34
SEH-1 #			SEO	2, 3	3	GBK22
				4		GBK32
SFH-1 #	SFO		2, 3	4	GBK22	
			4		GBK32	
SCH-2 *	8903		LO LXO	2, 3	20 AMP	GBK24
				4, 6		GBK34
				8		(2) GBK24
				10, 12		(1) GBK24
SCH-2 *			SMO	2, 3	30 AMP	(1) GBK34
				4		GBK24
SDH-1 *		SPO	2, 3	60 AMP	GBK24	
			4, 5		(1) GBK24	
SEH-1 *		SQO	2, 3	100 AMP	(1) GBK34	
			4, 5		GBK22	
SFH-1 *		SVO	2-3	200 AMP	(1) GBK32	
					200 AMP	GBK22

30072-002-72E

+ Enclosure not suitable for starters with Form B20 through B42.

Enclosure suitable for starters with melting alloy overload relay only.

* For contactors, replace reset assembly with closing plate, Class 9001, Type K51.