



### Main

For System M.

Battery-powered radio transmitter with 4 channels. For activating the Merten CONNECT radio system's radio receiver. A maximum of 12 radio receivers per channel can be connected.

Radio features: **System administrator**

### Complementary

Suitable for sticking onto walls or glass, screwing onto walls or flush-mounted outlets, or installing in a multiple combination. A flush-mounted box is not required.

#### Functions:

EASY CONNECT:

- Switch on, switch off, dim, raise/lower roller shutters

With CONNECT radio configuration tool:

- additionally toggle, push-button operation (bell), scenes, division of channels

**Channels:** 4

**Range:** up to 100 m free field, up to 30 m indoors

**Battery:** 1 lithium button cell (CR 2450N)

**Display elements:** LED for transmission confirmation/programming

**Receiver:** All receivers of the Merten CONNECT radio system.

Contents: Battery, retaining plate, double-sided adhesive strips, single-sided adhesive foils aluminium-coloured, screws, dowels.

Material : Thermoplastic brilliant

Colour: polar white, glossy