

# PlusLink-Moduls



## Display timer module



PlusLink

Version	Art. no.
Thermoplastic	
<input type="checkbox"/> lotus white	<b>MTN5755-6035</b>
<input checked="" type="checkbox"/> anthracite	<b>MTN5755-6034</b>
<input type="checkbox"/> sahara	<b>MTN5755-6033</b>
<input type="checkbox"/> stainless steel	<b>MTN5755-6036</b>
<input type="checkbox"/> nickel metallic	<b>MTN5755-6050</b>
<input type="checkbox"/> champagne metallic	<b>MTN5755-6051</b>
<input type="checkbox"/> mocca metallic	<b>MTN5755-6052</b>

For System Design.

For programmed and time-dependent switching of loads such as lighting or blind/roller shutter motors.

### Number of switching cycles (switching on/off, raising/lowering):

#### Switching, dimming, blind inserts:

- Per channel: 2 switching cycles / day

#### Central unit insert:

- Per PL line: 2 switching cycles / day

#### Functions:

- Pre-set switching times (in free groups)
- Menu-controlled operation
- Power reserve > 6 hours
- Reset to restore factory settings
- Random-check generator can be activated (in the range 0 - 30 mins)
- Astro function
- Simple to switch from summer to winter time
- Individual running time can be programmed
- Manual operation possible at any time
- Selectable arrow key function for push buttons or global scenes
- Setting the brightness values for the sun protection function
- Behaviour at wind alarm can be set

#### Local switching:

- Electronic switch insert
- Relay switch insert
- Electronic switch insert, 2-gang
- Relay switch insert, 2-gang

#### Local switching/dimming:

- Universal dimmer insert
- Control insert 1-10 V
- DALI control insert
- Universal dimmer insert, 2-gang

#### Controlling blinds/roller shutters locally:

- Blind control insert

#### Global switching, dimming, controlling blinds/roller shutters, retrieving scenes:

- Central unit insert

#### Operating elements: 5 buttons

#### Display elements: 5 LEDs, LCD display

#### Connection: Module interface

**To be completed with:** Central unit insert MTN5190-0000

Electronic switch insert MTN5151-00..

Electronic switch insert, 2-gang MTN5152-00..

Relay switch insert MTN5161-00..

Relay switch insert, 2-gang MTN5162-00..

Blind control insert MTN5165-0000

Universal dimmer insert MTN5171-00..

Universal dimmer insert, 2-gang MTN5172-00..

1-10 V insert MTN5180-00..

DALI insert MTN5185-00..

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.