



Instructions for :
**13A Switched Sockets
with clean Earth Facility**
with standard and non-standard
pin configurations

AR1621 Ed B

Ultimate 13A switched sockets with clean earth facility have two earth terminals. These can be linked for conventional earth installations, or used independently to provide a clean earth facility.

Non-standard switched sockets can be used where restricted access to the power supply is required. They accept 13A, 3-pin, non-standard plugs with 'T' shaped earth pins.

Conventional Linked Earth


Ensure the earth wire link remains fitted as supplied between the two terminals marked  and .


The earth conductors may be connected to either or both of these earth terminals.

2

Clean Earth

For a clean earth connection the earth wire link between the two earth terminals must be removed.

The circuit protective conductor and any metal back box bonding conductors must be connected to the terminal marked .

The clean earth conductor should be connected to the terminal marked .

Note: If in doubt on how to proceed, consult a qualified electrician.

3