



Main

For Artec, Tracent, Antique.

Battery-powered radio transmitter with 2 channels. For activating the Merten CONNECT radio system's radio receiver. A maximum of 12 radio receivers per channel can be connected.

Radio features: **System administrator**

Complementary

Suitable for sticking onto walls or glass, screwing onto walls or flush-mounted outlets, or installing in a multiple combination. A flush-mounted box is not required.

Functions:

EASY CONNECT:

- Switch on, switch off, dim, raise/lower roller shutters

With CONNECT radio configuration tool:

- additionally toggle, push-button operation (bell), scenes, division of channels

Channels: 2

Range: up to 100 m free field, up to 30 m indoors

Battery: 1 lithium button cell (CR 2450N)

Display elements: LED for transmission confirmation/programming

Receiver: All receivers of the Merten CONNECT radio system.

Contents: Battery, retaining plate, double-sided adhesive strips, single-sided adhesive foils aluminium-coloured, screws, dowels.

Material : Thermoplastic brilliant

Colour: white, glossy