Product data sheet Characteristics

8539SFW42V06 COMBO STARTER 600VAC 135A NEMA



by Schneider Electric

Price*: 13208.00 USD
Commercial status
This Product is Obsolete:

⚠ This Product is Obsolete

Main

Contactor application	Non-reversing	
Control circuit	Common control circuit	
Device short name	S	
Disconnector device type	Mag-Gard circuit breaker	
Enclosure type	Enclosure corrosion resistance indoor/outdoor Enclosure water resistant indoor/outdoor Enclosure dustproof indoor/outdoor	

Complementary

Rated current	135 A
System Voltage	480 V AC 60 Hz 440 V AC 50 Hz
Depth	10.53 in
Device mounting	Surface
Electrical connection	Screw clamp terminal
Enclosure material	Brushed stainless steel
Height	52.5 in
Motor power hp	30 hp 200 V AC
	6075 hp 460 V AC
	60100 hp 575 V AC
NEMA size	4
Network number of phases	3 phases
Number of poles	3
Number of thermal units required	3
Permissible voltage	<= 600 V AC
Product destination	Circuit breaker KAL3625025M
Product weight	120 lb(US)
Short-circuit protection	22000 A AIR
Thermal overload type	Melting alloy
Width	16 in

Environment

NEMA degree of protection	NEMA 4/4X
Product certifications	UL listed file E152395 CCN NKJH7

Ordering and shipping details

Category	21218 - 8538,39 W/STAINLESS ENCLOS
Discount Schedule	CP1
Nbr. of units in pkg.	1
Package weight(Lbs)	120
Returnability	N

Offer Sustainability

RoHS (date code: YYWW)	Will not be compliant
REACh	Reference not containing SVHC above the threshold

Contractual warranty

warranty period To months	Warranty period	18 months
---------------------------	-----------------	-----------

Product Life Status : End of commercialisation

