

Product data sheet

Characteristics

8903PBN11BV39

panelboard lighting contactor, 75 AMP, 3 pole,
bus mount, 240/277 60Hz coil



Product availability: Non-Stock - Not normally stocked in distribution facility



Main

| | |
|---------------------------|--------------------------------------|
| Product or component type | Mechanically Held Lighting Contactor |
| Device short name | PB |
| Control circuit | Common control circuit |

Complementary

| | |
|-------------------------------|--|
| [Uc] control circuit voltage | 240/277 V AC at 60 Hz |
| [In] rated current | 75 A |
| Poles description | 3P |
| AWG gauge | AWG 1/0 (aluminium/copper) , power wire AWG 18...AWG 10 (copper) , control wire |
| System Voltage | 600 V AC |
| Auxiliary contact composition | Without |
| Mounting support | Busbar |
| Electrical connection | Busbar connection |
| Height | 8.31 in (211 mm) |
| Depth | 3.39 in (86 mm) |
| Width | 7.52 in (191 mm) |

Environment


| | |
|------------------------|------------------|
| Product certifications | CSA UL listed |
|------------------------|------------------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Ordering and shipping details

| | |
|-----------------------|-----------------|
| Category | 21323 - 8903 PB |
| Discount Schedule | CP1 |
| Nbr. of units in pkg. | 1 |
| Package weight(Lbs) | 25 |
| Returnability | N |
| Country of origin | MX |

Offer Sustainability

| | |
|---------------------------|--|
| RoHS (date code: YYWW) | Compliant - since 1545 - Schneider Electric declaration of conformity  Schneider-Electric declaration of conformity |
| California proposition 65 | WARNING: This product can expose you to chemicals including: |
| ----- Substance 1 | Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. |
| ----- More information | For more information go to www.p65warnings.ca.gov |

Product Life Status : **Commercialised**