



Main

For switching two loads via make contact. Can be remote-controlled via Merten CONNECT radio system transmitters.
Radio features: **router**

Complementary

Suitable for installation into a size 60 installation box. With snap-off mounting plates.
With screw terminals.

Functions:

EASY CONNECT:

- 1. Channel can be used, switch on, switch off, toggle
- With CONNECT radio configuration tool:
- 2. additionally staircase lighting function, ON/OFF delay

Nominal voltage: AC 230 V

Nominal current: 6 A

Connected loads:

Incandescent lamps: AC 230 V, 600 W

Halogen lamps: AC 230 V, 600 W

Display elements: LED for status display

Operating elements: Push-button for local operation and programming

Dimensions: 48 x 52 x 27 mm (H x W x D)

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.